

BLE-CC41-A Bluetooth Module

SPECIFICATION



1. Overview



BLE-CC41-A is a next-generation, class 2, Bluetooth 4.0 module. Support the AT command, the user can according to need to change the baud rate of serial port, name of equipment, matching parameters such as password, use agile.BLE-CC41-A is a highly integrated and sophisticated Bluetooth module, containing all the necessary elements .Therefore BLE-CC41-A provides an ideal solution for developers who want to integrate Bluetooth wireless technology into their designs with limited knowledge of Bluetooth and RF technologies.

BLE-CC41-A module combined with Bolutek's complete development, testing and verification services and excellent developer support, OEMs and designers ensure that their products reach the market rapidly and cost-efficiently in relation to time and resources. Bolutek has extensive in-house knowledge of both software and hardware offering customers a single point of contact to all Bluetooth related issues.

2. Feature

Bluetooth protocol: Bluetooth Specification V4.0 BLE, send and receive no byte limit, open environment and iphone 4 s can achieve 110 meters extreme distance communication. Based on TI CC2541 chipset Bluetooth class 2 Industrial level SPP Bluetooth module Integrated chip antenna Size: 26.7 x 13 x 2 mm Industrial temperature range from -40° C to $+85^{\circ}$ C Support for on-board applications Operating frequency: 2.4 GHz ISM band Modulation method: GFSK (Gaussian Frequency Shift Keying) Acuity: - 84 DBM or less BER at 0.1% Transfer rate: Asynchronous: 6 KBPS Synchronous: KBPS Security features: Authentication and encryption Support services: Central and Peripheral UUID FFE0, FFE1



Power consumption: automatic sleep mode, the standby current 400 ~ 1.5 mA, transfer 8.5 mA. Power supply: + 3.3 VDC 50 ma RoHS BQB compliant

3. Application Fields

Cable replacement Point-of-sales systems Barcode readers and pay terminals Telemetry and machine-to-machine devices Logistics and transportation systems Automotive inspection and measurement systems Medical systems Fitness and sports telemetry devices PDA and other portable terminals PCs and laptop OBD

4. Physical Characteristics

Operating Frequency Band	2.4GHz ISM band
Bluetooth Specification	BLE4.0
Output Power Class	Class 2
Operating Voltage	3.3V
Host Interface	UART
Dimension	27mm (L) x 13 (W) mm x 2mm (H)

5. Electrical Characteristics

Absolute Maximum Ratings		
Rating	Min	Max
Storage temperature	-40°C	+150°C
Supply voltage: VBAT	-0.4V	5.6V
Other terminal voltages	VSS-0.4V	VDD+0.4V

Recommended Operating Conditions			
Operating Condition	Min	Max	
Operating temperature range	-40°C	+150°℃	
Guaranteed RF performance range ^(a)	-40°C	+150°℃	
Supply voltage: VBAT	2.2V	4.2V ^(b)	



6. Application Circuit Diagram



Note: This application circuit for the Bluetooth serial port circuitry, such as the need for other application, please contacts <u>Bolutek</u>.

PIN NO.	NAME	FUNCTION
1	UART-TX	UART Data Output
2	UART-RX	UART Data Input
3	UART-CTS	UART Clear To Send Active Low
4	UART-RTS	UART Request To Send Active Low
5	NC	NC
6	NC	NC
7	P2_2	Debug the clock
8	P2_1	Debug the data
9	P2_0	Programmable Input/Output Line
10	NC	NC

7 .Pin Configurations



BOLUTEK BLE-CC41-A Bluetooth Module

11	RESETB	Reset if low Input debounced so must below for>5ms to	
		cause a reset	
12	VCC	+3.3V Supply	
13	GND	Ground	
14	GND	Ground	
15	SDA	Data port	
16	NC	NC	
17	NC	NC	
18	NC	NC	
19	NC	NC	
20	SDL	Clock port	
21	GND	Ground	
22	GND	Ground	
23	P1_3	SW1 system key, see Other configuration	
24	P1_2	State instructions LED, see Other configuration	
25	P1_1	Programmable Input/Output Line	
26	P1_0	Programmable Input/Output Line	
27	P0_7	Programmable Input/Output Line	
28	P0_6	Programmable Input/Output Line	
29	P0_5	Programmable Input/Output Line	
30	P0_4	Programmable Input/Output Line	
31	P0_3	Programmable Input/Output Line	
32	P0_2	Programmable Input/Output Line	
33	P0_1	Programmable Input/Output Line	
34	P0_0	Programmable Input/Output Line	



8. Contour Dimension



9. Other configuration

State Instructions LED: P1_2

Model	LED Display	Status
Even slow flash Slave (800ms-on,800ms-off)		Waiting for matching
	Long bright	connection

Module dormancy set

Is only meaningful in from dormancy mode module, from the mode via a serial port to send "AT + SLEEP", if no accident, the module will return "OK" and enter a dormant state, this state to be found and connection status.

Wake up the module Settings

There are two ways:

Method one: you can send the length of the string is greater than or equal to 80 to activate the module. Send the activated string cannot contain the AT command, success after WAKE up, a serial port will output "+ WAKE OK" string. Method 2: short press the system button SW1.



System key SW1(P1_3)

P1_3 for input pin, short press control, can realize the following functions:

1, the module is in a state of dormancy:

Module will be awakened to the normal state, the success after WAKE up, a serial port will output "+ WAKE OK" string.

2, the module is in a state of connection:

Disconnected module will initiate the request.

10.Layout Announcements

1, BLE-CC41-A bluetooth module serial level should be 3.3 V, if the connection and 5V level system need to increase the level conversion chip.

2, Bluetooth signal is highly affected by the surrounding, such as trees, metal, wall can have certain absorption on the bluetooth signal or block, so the installation is not recommended in the metal case.

3, Due to metal will weaken the function of antenna, it is suggested that Lay in the module board, don't lay GND and a line under the antenna module, it is best to hollow out.

11. Contact us

Shenzhen Bolutek Technology Co.,Ltd. Addr: Building B, Area A, the Internet Industry base of BaoAn District, Shenzhen, Guangdong, China Tel: 86-755-26509941 Fax: 86-755-26509942 Email: sales@bolutek.com http://www.bolutek.com