



JDM® Six Zone Mixer Amplifier With Output Attenuators

Housed in a heavy duty 3RU rack mount cabinet, these mixer amplifiers include a host of features and are ideally suited for schools, offices, medical suites, office/factory units etc. Each of the first three inputs can be configured for either microphone or auxiliary use, whilst the last two are for dedicated auxiliary use. Along with this, the amplifier provides 6 output zones with individual in-built attenuators. Each zone is able to be activated on or off via the front panel switches. LEDs indicate when each zone is selected. All zones can be selected on via the "all call" switch.

Front panel controls are provided for volume, treble and bass for each input, along with a master volume control. Output level is monitored via the front panel LED VU meter.

Fitted with paging chime and siren tone generator. A telephone paging input is also included. The front panel has provision for fitting optional modules such as, **A 4344A** tuner or **A 4346** CD/MP3 player/Tuner. Operation is from either 240V AC or 24V DC.

Other features include record out socket, pre amp, in/out socket to feed other power amplifiers or insert other effects equipment such as a graphic equalizer.

The amplifier design includes comprehensive protection circuitry for over current, over temperature and short circuits.

The addition of the optional **A 4353** 6 zone paging microphone and **A 4352** control PCB, enables paging to each or any combination of speaker zones remotely.



Rear panel shown with tuner connections fitted (See A 4344 & A 4346 below)

SPECIFICATIONS

A 4330 Power:	120 watts RMS
A 4332 Power:	240 watts RMS
A 4336 Power:	480 watts RMS
Distortion:	< 1% @ 1kHz
Signal to Noise Ratio	Line: >70dB Mic: >60dB
Frequency Response	80Hz - 15kHz, ±3dB
Mic input sensitivity:	3mV balanced
Line inputs sensitivity:	300mV
Telephone input	245mV
Bass:	±10dB @ 100Hz
Treble:	±10dB @ 10kHz
Power supply:	240V AC or 24V DC
Dimensions:	≈430W x 352D x 133H mm
A 4330 Weight:	13kg
A 4332 Weight:	14kg
A 4336 Weight:	20kg

Features • 5 inputs • 6 output zones • Direct 100V line output • 4Ω output • Individual zone attenuators (max 80W) • 24V DC operation • LED VU meter • 2 year warranty • Volume, treble and bass controls for each input • Over current protection • Over temperature protection • Short circuit protection • Telephone paging input • Phantom power • Selectable microphone priority

Price Each	RRP	2+
A 4330 120W	1395.00	1259.00
A 4332 240W	1595.00	1440.00
A 4336 480W	1995.00	1885.00

JDM® Accessories

CD/MP3 Tuner Module



A plug-in combination AM/FM tuner and CD/MP3 player module. Suits all JDM® public address amplifiers. Tuner features 30 station presets. 1 year warranty. Includes rear connection panel.

Features • Audio CD & MP3 CD playback • Random, repeat functions • Adjustable output level • Track cue function • CD-R, CD-RW compatible

Price Each	RRP	2+
A 4346	699.00	675.00

AM/FM Tuner & USB Player Module



A plug-in AM/FM tuner & USB audio player module to suit all JDM® public address amplifiers. Features 18 station presets and adjustable output level. Includes rear connection panel.

Features • 18 station presets • AM/FM • Inbuilt level control • Auto seek tuning • LCD readout • Easy plug-in installation for all JDM® amplifiers.

Price Each	RRP	2+
A 4344A	279.00	265.00

6 Zone Paging Console



The optional **A 4352** control PCB and **A 4353** paging console allows remote paging to the above JDM® public address amplifiers (not suitable for A 4320-4). The control PCB is fitted internally to the amplifier. The sturdy all metal paging console connects to the A 4352 via standard Cat 5e cabling. It allows paging to individual zones, or combination of zones. Plus an 'all-call' button. Up to 3 mic consoles may be daisy-chained to allow zone paging from several remote locations. In built auxiliary input allows a remote music source to be played to selected zones. Maximum cable distance from furthest mic console to amplifier cannot exceed 1000m.

Note: for remote paging applications you require one A 4352 control PCB and up to three A 4353 paging consoles.

Price Each	RRP	2+
A 4353 Paging Console	299.00	275.00
A 4352 Control PCB	119.00	109.00

Important Note For Wholesale Customers

All prices listed in this catalogue are RRP "retail" prices. To access our competitive wholesale pricing scheme apply for an account via www.altronics.com.au or phone the wholesale division in your state - see back cover for phone numbers..